


## 23 Exhibition Drive, Malaga Western Australia

Monday - Friday 7am-5pm + Sat 8am-4pm

Sales Centre for Sales, Advice + Orders T +61 8 9209 7400 hello@beyondtools.com

## 18V BLUETOOTH & DAB WORKSITE RADIO BARE (TOOL ONLY) GPB 18V-2 SC (06014A3140) BY BOSCH





Extreme flexibility for pleasant working: sourcing from DAB+, Bluetooth  $^{\circledR}$ , FM, and AUX

Features intuitive operation and quick setup in combination with a handle and hook for vertical and horizontal placement Unique stereo sound due to the possibility to couple two radios with one smartphone

## **Specifications:**

Radio frequency range FM: 87.5 – 108 MHz Radio frequency range DAB+: 174.928 – 239.2 MHz

Station presets FM: 8 Station presets DAB+: 8 Input voltage(s), battery: 18V Station presets: 16

Input voltage(s), mains: 100 â€" 240V Output voltage(s), mains: 18V

Rated power of amplifier (in mains operation): 15W

**Includes:** Cardboard box

 $1 \times DC$ -in power adapter (spare part number  $1 \ 619 \ PB4 \ 902)$ 

1 x AUX cable

1 x 3 V CR2032 lithium button cell battery



| 8729488 | 06014A3140 | \$319 |
|---------|------------|-------|
|         |            |       |
| Model   |            |       |

| Model                             |  |
|-----------------------------------|--|
| Туре                              | Radio  |
| SKU                               | 8729488  |
| Part Number                       | 06014A3140   |
| Barcode                           | 4059952556178  |
| Brand                             | Bosch  |
| Technical - Main                  |  |
| Battery Voltage (V)               | 18V  |
| Water Protection Rating           | IP54   |
| Connectivity                      |  |
| AUX Enabled                       | ✓  |
| Bluetooth® Enabled                | ✓  |
| Features                          |  |
| FM Radio Broadcasting             | ✓  |
| Digital Audio Broadcasting (DAB+) | ✓  |
| USB Charging Port                 | ✓  |
| Standard Inclusions               | 1 x DC-in power adapter (spare part number 1 619 PB4 902), 1 x AUX cable, 1 x 3 V CR2032 lithium button cell battery |
| Packaging + Shipping              |  |
| Shipping Weight (Gross)           | 1.48 kg  |